


# Sublime accessories

## Power supplies

### SL-PWR-40

#### Power supply



40W power supply for VikinX Sublime router series

#### Specifications for SL-PWR-40

|                         |  |
|-------------------------|--|
| SL-PWR-40               | 40W power supply unit for 8x8 – 32x32 versions                           |
| AC Supply voltage range | 100 – 240VAC, 50 – 60Hz<br>Max 1.6A                                      |
| AC Mains connector      | IEC 320  |
| DC output:              | +15V, max. 2.2A/-15V, max 1.35A.<br>Maximum 43W for 8x8 – 32x32 versions |
| DC connector            | D-sub 9-pin male   |
| Status monitoring       | Via LED in front of the router/CP  |
| Safety standards        | Compliant with CE EN60950, UL-1950/CSA22.2                               |

### SL-PWR-90

#### Power supply



90W power supply for VikinX Sublime router series

#### Specifications for SL-PWR-90

|                         |   |
|-------------------------|---|
| SL-PWR-90               | 90W power supply unit for 64x64 versions                        |
| AC Supply voltage range | 100 – 240VAC, 50 – 60Hz<br>Max 3A                               |
| AC Mains connector      | IEC 320   |
| DC output:              | +15V, max. 4A/-15V, max 2.5A.<br>Maximum 90W for 64x64 versions |
| DC connector            | DE9   |
| Status monitoring       | Via LED in front of the router/CP                               |
| Safety standards        | Compliant with CE EN60950, UL-1950/CSA22.2                      |

### SL-PWR-300

#### Power supply



300W power supply for VikinX Sublime router series

#### Specifications for SL-PWR-300

|                         |  |
|-------------------------|--|
| SL-PWR-300              | 300W power supply unit for 64x64 versions          |
| AC Supply voltage range | 90 – 130VAC/180 – 254VAC, switchable,<br>50 – 60Hz |
| AC Mains connector      | IEC 320  |
| DC output:              | +48V, max 6.25A. Maximum 300W                      |
| DC connector            | DSUB 2V2P  |
| Status monitoring       | Via LED in front of the router/CP                  |
| Safety standards        | Compliant with CE EN60950, UL-1950/CSA22.2         |

#### Ordering options


|                  |  |
|------------------|--|
| 12450 SL-PWR-40  | 40W power supply for Sublime series of routers and panels, |
| 12876 SL-PWR-90  | 40W power supply for Sublime series of routers and panels, |
| 19017 SL-PWR-300 | 300W AC power supply unit for Sublime 128 range.           |

# Sublime accessories

## Accessories

### SL-MT-2PSU

### Mounting tray



1 RU tray for 2x SL-PWR-40 or 1x SL-PWR-90, to be placed behind the VikinX Sublime router

### DB25PIN

### Adaptor



Small print-card with DB25 to screw-terminal

### SL-MT-6PSU/12615 SL-MT-BP

### Mounting tray and blindplate



1 RU mounting tray for 6x SL-PWR-40 or 3x PWR-90  
Blindplate for 2 positions of SL-MT-6PSU

### 3MXXLRF-25PIN

### Cable



Audio breakout cable  
DB25 PIN XLRF, 3 meter cable

### 3MXXLRM-25PIN

### Cable



Audio breakout cable  
DB25 PIN XLRM, 3 meter cable

### Ordering options

|                     |   |
|---------------------|---|
| 12613<br>SL-MT-2PSU | 19" 1RU tray for 2x SL-PWR-40/<br>SL-PWR-90; to be placed behind<br>Sublime router. |
|---------------------|---|

|                     |  |
|---------------------|--|
| 12614<br>SL-MT-6PSU | 9" 1RU mounting tray for 6x SL-PWR-40<br>or 3x SL-PWR-90; or a combination of<br>both. |
|---------------------|--|

|                   |   |
|-------------------|---|
| 12615<br>SL-MT-BP | Blank Plate for 2 positions of<br>SL-MT-6PSU. |
|-------------------|---|

|                        |                         |
|------------------------|-------------------------|
| 11543<br>3mxXLRF-25pin | DB25pin XLRF, 3m cable. |
|------------------------|-------------------------|

|                        |                         |
|------------------------|-------------------------|
| 11546<br>3mxXLRM-25pin | DB25pin XLRM, 3m cable. |
|------------------------|-------------------------|

|               |  |
|---------------|--|
| 11071 DB25PIN | Small print-card with DB25 to<br>screw-terminal. |
|---------------|--|